

# **AUTOMATIC TURN SIGNAL SHUT OFF 3 TECH SHEET**

**PLEASE MAKE SURE THE CUSTOMER RECEIVES A COPY OF THIS INFO , AND OPERATION INFORMATION !**

**READ THIS BEFORE YOU INSTALL THIS MODULE !**

**THIS MODULE IS DESIGNED FOR HARLEY-DAVIDSONS , OR CUSTOM BIKES ! IT ONLY WORKS WITH MOMENTARY TURN SIGNAL BUTTONS THAT ACTIVE MOMENTARILY !**

**THERE ARE 2 SETS OF INSTRUCTIONS IN THIS PACKAGE , YOU NEED TO PICK ONE AND ONE ONLY ! EITHER YOUR BIKE IS EQUIPPED WITH OEM ( ORIGINAL EQUIPMENT MANUFACTURER ) WIRING , OR IT ISN'T. IF IT IS BONE STOCK , USE " INSTRUCTIONS FOR OEM WIRING " SHEET .**

**IF THE BIKE HAS BEEN MODIFIED AT ALL , CUSTOM WIRED OR A CUSTOM BUILT BIKE , YOU NEED TO USE THE CUSTOM BIKES / CUSTOM WIRING DIAGRAM . IF YOU ARE INSTALLING THIS ON A CUSTOM MANUFACTURED BIKE OR RUNNING WIRES FROM SCRATCH , YOU WILL ALSO USE THE CUSTOM BIKES / CUSTOM WIRING DIAGRAM .**



## **FEATURES & OPERATION :**

**THIS MODULE WILL ALLOW YOUR TURN SIGNALS TO FLASH FOR 9 SECONDS AND THEN WILL AUTOMATICALLY CANCEL THE TURN SIGNALS . A MOMENTARY BLIP OF THE TURN SIGNAL BUTTON AND THE MODULE WILL DO THE REST .**



**IF YOU MAKE A QUICK LANE CHANGE , BLIP THE BUTTON A SECOND TIME , THIS WILL DISCONTINUE THE 9 SECOND TIMED FLASHING .**



**TO GAIN ADDITIONAL TIME , ( LONG LIGHT ) MERELY BLIP THE BUTTON AGAIN ONCE YOUR ON THE ROLL .**



**THIS MODULE HAS A BUILT IN EMERGENCY FLASHER MODE , DEPRESS BOTH BUTTONS SIMULTANEOUSLY, THEN LET OFF SIMULTANEOUSLY . REPEAT THIS SEQUENCE TO SHUT OFF THE EMERGENCY FLASHER MODE .**



**THIS MODULE HAS A BUILT IN SOLID STATE FLASHER .**



**THIS MODULE HAS THE " LOAD EQUALIZER III " BUILT IN AND WILL RUN A SINGLE STRIP OF LED TURN SIGNALS , ALL THE WAY UP TO 100 WATTS OF TURN SIGNAL COMBINATIONS , PER SIDE . DO NOT RUN MORE THAN 100 WATTS PER SIDE . IF YOU DO , OUR TEST BOARD CAN DETECT THIS , AND WILL VOID THE WARRANTY OF THIS MODULE .**

**WWW.BADLANDSMOTORCYCLEPRODUCTS.COM**